


EXTECH[®] USER MANUAL

Model ET10 GFCI Receptacle Tester



Standard Receptacle

1. Always test on a known good circuit before use.
2. Refer all indicated problems to a qualified electrician.
3. Lights will indicate circuit condition: Correct, Open Ground, Open Neutral, Open Hot, Hot/Ground Reversed, or Hot/Neutral Reversed.
4. The tester will not indicate the quality of the ground connection, 2 hot wires in a circuit, a combination of defects, a combination of defects, or reversal of ground and neutral conductors.

GFCI Receptacle

1. Before using the tester, press the TEST button on the installed GFCI receptacle, the GFCI should trip. If it does not, do not use the circuit and call a qualified electrician. If it does trip, press the RESET button on the receptacle and plug in the tester.
2. Verify that the wiring is correct.
3. Press and hold the test button on the tester for at least 6 seconds, the indicator lights on the tester will shut off when the GFCI trips.
4. If the circuit does not trip, either the GFCI is operable but the wiring is incorrect, or the wiring is correct and the GFCI is inoperable.
5. When testing a GFCI installed in a 2-wire (non-grounded) system, the tester may indicate a faulty GFCI. If this occurs, press the TEST and RESET buttons on the GFCI to determine proper operation.
6. GFCI test current is 6~9mA.

OPEN GROUND	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
OPEN NEUTRAL	<input type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>
OPEN HOT	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
HOT & GND REV	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>
HOT & NEU REV	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>
CORRECT WIRING	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

Two-year Warranty

Teledyne FLIR LLC warrants this Extech brand instrument to be free of defects in parts and workmanship for **two years from date of shipment (a six-month limited warranty applies to sensors and cables). To view the full warranty text please visit: <http://www.extech.com/support/warranties>.**

Calibration and Repair Services

Teledyne FLIR LLC offers calibration and repair services for the Extech brand products we sell. We offer NIST traceable calibration for most of our products. Contact us for information on calibration and repair availability, refer to the contact information below. Annual calibrations should be performed to verify meter performance and accuracy. Product specifications are subject to change without notice. Please visit our website for the most up-to-date product information: www.extech.com.

Contact Customer Support

Customer Support Telephone List: <https://support.flir.com/contact>

Calibration, Repair, and Returns: repair@extech.com

Technical Support: <https://support.flir.com>

Copyright © 2021 Teledyne FLIR LLC

All rights reserved including the right of reproduction in whole or in part in any form
www.extech.com